



FOR TYPICAL REMOTE CONTROL
DETAILS SEE DOCUMENT
RWS300

VOLTAGE OPTIONS

VOLTAGE
110VDC
48VDC
24VDC

FUSE FS1 - 6A ANTI-SURGE

NOTE

DEFAULT FOR SLEEP MODE IS ENABLE TO DISSABLE SLEEP MODE CONNECT 5 TO 46 & 4 TO 47. ACTUATOR WILL REMAIN POWERED UP AT ALL TIMES WHILE SUPPLY IS PRESENT SLEEP MODE CAN ALSO BE DISABLED BY MOVING LINK LK1 FROM SOLAR TO NORM. 24VDC WILL BE LOST WHEN IN SLEEP MODE. IF CUSTOMER SUPPLY IS NEEDED TO WAKE ACTUATOR LINK LK2 MUST BE MOVED TO CUST PERM FOR MAINTAINED CUSTOMER SUPPLY.

MAX EXTERNAL LOAD ON TERMINALS 4 & 5 TO BE 5W.

REFER TO PUBLICATION E170E FOR APPROVED FUSES FS1 AND FS2.

CONTROL SIGNAL THRESHOLD VOLTAGES TO BE MINIMUM 'ON' 20V AC/DC MAXIMUM 'OFF' = 3V MINIMUM CONTROL SIGNAL DURATION TO BE 4 SECOND.

CURRENT DRAWN FROM EACH REMOTE CONTROL SIGNAL IS 5mA ON 24V DC OR 12mA ON 120V AC

WIRES ARE IDENTIFIED AT EACH END BY TERMINAL No. OR TAG No.

INDICATION CONTACTS S1-S4 ARE SHOWN IN THEIR DEFAULT CONFIGURATION. CONTACTS MAY BE CONFIGURED FOR ANY OF THE FUNCTIONS DESCRIBED IN E170E

No	DATE	REVISION DETAILS
02	070907 P.J.W	MINIMUM CONTROL SIGNAL DURATION WAS 1 SECOND CHANGED FOR IOPRO MAIN PCB WAKE UP TIME. CHECKED M.H

www.rotork.com

ROTORK CONTROLS LTD BATH, BA1 3JQ ENGLAND Tel:01225-733200	ROTORK CONTROLS INC ROCHESTER NY 14624, USA Tel:585-328-1550
---	---

CONFIG BY PJW
DATE 090306
CHECKED DA
BASE WD --
JOB No --
M.I.No .

**IQ DC + TWO SPEED
TIMER**

CIRCUIT DIAGRAM No -REV
3002-010-02

B1 C1 B2 C2