

SIL NOTES (Superseding Sheet 2 Notes)

Independently Certified to IEC61508-2 (2010) as an element suitable for use in safety related systems up to and including SIL 2 (1001) and SIL 3 (1002). Must be installed, commissioned, tested and operated fully in accordance with the Safety Manual. Refer to SIL Safety Manual - PUB002-057

SIL STAYPUT (Safety Function 1): The control signal must be applied to terminal 34 before an open or closed control signal will operate the actuator. This is a high demand safety function, actuator will not move spuriously.


If the safety function is configured for SIL STAYPUT only, terminal 25 will be a standard (Non-SIL) ESD terminal, as per PUB002-040.

SIL MOVE TO LIMIT (Safety Function 2): The control signal must be removed to terminal 25 to cause the actuator to move to the configured end of travel position (Open or Close limit). This is not a maintained input, SF2 control signal must be removed for the duration of operation to the configured limit position. This is a low demand safety function.

If the safety function is configured for SIL MOVE TO LIMIT (SF2) ONLY, terminal 34 will be a standard Stop/Maintain input in accordance with PUB002-041. **Safety Function 1 + Safety Function 2**: Where both safety functions are required, the priority and functions must be configured in accordance with the SIL Safety Manual - PUB002-057. The common for SF1 (terminal 36) and SF2 (terminal 31) are independent allowing the control signal to be derived from separate, independent systems. If required, where signals are derived from the same system, the commons can be linked together.

SF1 and SF2 Signals must be within the range 16-60VDC, positive supply switched only.

L	of 1 and of 2 digitals mast be within the range 10 00 VDG, positive supply switched only.										
	lss	<u>Date</u>	Chkd	Revision Details	rot	OFK	IQ + SIL + FOLOMATIC & CPT + RHS				
		170519		FIRST ISSUE	www. <b>rotork</b> .com		_				
		101219		Relays S3-S4 corrected Spelling mistake corrected	ROTORK CONTROLS LTD	ROTORK CONTROLS INC	Drawn by: PJW	Circuit Diagram Number		Sheet	
	۱	101213	FJVV	Spelling mistake corrected	,	ROCHESTER	Date : 170519 Base WD: 703B0006	703B0006	No	1	
					-	NY 14624, USA	Job No :		3	of 2	
- 1					Tel:01225-733200	Tel:585-247-2304	MI No ·	B1 C1 B2 C2	1 1		



IQ: